

Features

- Attenuation: 0.5 dB Steps to 15.5 dB
- Temperature Stability: ± 0.18 dB from -55°C to $+85^{\circ}\text{C}$ Typical
- Low DC Power Consumption
- Hermetic Surface Mount Package
- Integral TTL Driver
- $50\ \Omega$ Nominal Impedance
- Lead-Free CR-12 Package
- 260°C Reflow Compatible
- RoHS* Compliant

Description


M/A-COM's AT-283-PIN is a GaAs FET 5-bit digital attenuator with a 0.5 dB minimum step size and 15.5 dB total attenuation. This attenuator and integral TTL driver is in a hermetically sealed ceramic 16 lead surface mount package. The AT-283-PIN is ideally suited for use where accuracy, fast switching, very low power consumption and low intermodulation products are required. Typical applications include dynamic range setting in precision receiver circuits and other gain/leveling control circuits. Environmental screening is available. Contact the factory for information.

Ordering Information

| Part Number | Package |
|--------------------|-------------------|
| AT-283-PIN | Bulk Packaging |
| MAAD-007229-0001TR | 1000 piece reel |
| MAAD-007229-0001TB | Sample Test Board |

Note: Reference Application Note M513 for reel size information.

Functional Schematic



Pin Configuration

| Pin No. | Function | Pin No. | Function |
|---------|----------|---------|----------|
| 1 | RF1 | 9 | C5 |
| 2 | GND | 10 | +5V |
| 3 | GND | 11 | -5V |
| 4 | GND | 12 | C4 |
| 5 | GND | 13 | C3 |
| 6 | GND | 14 | C2 |
| 7 | GND | 15 | C1 |
| 8 | RF2 | 16 | GND |

The metal bottom of the case must be connected to RF and DC ground.

1 * Restrictions on Hazardous Substances, European Union Directive 2002/95/EC.

Electrical Specifications: $T_A = 25^\circ\text{C}^1$

| Parameter | Test Conditions | Units | Min | Typ | Max |
|---|---|--------------------------|---|-----|-------|
| Reference Insertion Loss | DC-0.5 GHz | dB | — | — | 2.2 |
| | DC-1.0 GHz | dB | — | — | 2.5 |
| | DC-2.0 GHz | dB | — | — | 2.9 |
| Attenuation Accuracy ² | Any Single Bit Any Combination of Bits | DC-2.0 GHz DC-2.0 GHz | ± (0.25 +3% of attenuation setting in dB) dB ± (0.25 +3% of attenuation setting in dB) dB or ± 0.4 dB, whichever is greater | | |
| VSWR | DC-1.0 GHz | — | — | — | 1.6:1 |
| | DC-2.0 GHz | — | — | — | 1.7:1 |
| Trise, Tfall Ton, Toff Transients | 10% to 90% | nS | — | 10 | — |
| | 50% Control to 90/10% RF | nS | — | 27 | — |
| | In-band (peak—peak) | mV | — | 22 | — |
| 1 dB Compression ³ | Input Power | 0.05 GHz | — | +20 | — |
| | Input Power | 0.5-2.0 GHz | — | +28 | — |
| Input IP ₃ ³ | For two-tone input power up to +5 dBm | 0.05 GHz 0.5-2.0 GHz | — | +40 | — |
| | | | — | +47 | — |
| Input IP ₂ ³ | For two-tone input power up to +5 dBm | 0.05 GHz 0.5-2.0 GHz | — | +53 | — |
| | | | — | +68 | — |
| V _{CC} | — | V | 4.5 | 5.0 | 5.5 |
| V _{EE} | — | V | -8.0 | — | -5.0 |
| I _{CC} | V _{CC} = 4.5 to 5.5V V _{ctl} = 0 to 0.8V, or V _{CC} - 2.1V to V _{CC} | mA | — | — | 5.0 |
| I _{EE} | V _{EE} = -5.0 to -8.0V | mA | — | — | 1.0 |
| V _{ctl} | Logic 0 (TTL) | V | 0.0 | — | 0.8 |
| | Logic 1 (TTL) | V | 2.0 | — | 5.0 |
| Input Leakage Current (Low) | 0 to 0.8V | µA | — | — | 1.0 |
| Input Leakage Current (High) | 2.0 to 5.0V | µA | — | — | 1.0 |

1. All specifications apply when operated with bias voltages of +5.0V for V_{CC} and -5.0V to -8.0V for V_{EE}, and 50 Ω impedance at all ports unless otherwise specified.
2. This attenuator is guaranteed monotonic.
3. V_{EE} = -5.0V for the typical numbers given.

Absolute Maximum Ratings ^{4,5}

| Parameter | Absolute Maximum |
|--|---|
| Maximum Input Power 0.05 GHz 0.5-2.0 GHz | +27 dBm +34 dBm |
| V_{CC} | $-0.5V \leq V_{CC} \leq +7.0V$ |
| V_{EE} | $-8.5V \leq V_{EE} \leq +0.5V$ |
| $V_{CC} - V_{EE}$ | $-0.5V \leq V_{CC} - V_{EE} \leq 14.5V$ |
| V_{in}^6 | $-0.5V \leq V_{in} \leq V_{CC} + 0.5V$ |
| Operating Temperature | $-55^{\circ}C$ to $+125^{\circ}C$ |
| Storage Temperature | $-65^{\circ}C$ to $+150^{\circ}C$ |

- Exceeding any one or combination of these limits may cause permanent damage to this device.
- M/A-COM does not recommend sustained operation near these survivability limits.
- Standard CMOS TTL interface, latch-up will occur if logic signal is applied prior to power supply.

Handling Procedures


Please observe the following precautions to avoid damage:

Static Sensitivity


Gallium Arsenide Integrated Circuits are sensitive to electrostatic discharge (ESD) and can be damaged by static electricity. Proper ESD control techniques should be used when handling these devices.

Typical Performance Curves

Reference Insertion Loss vs. Frequency @ Temperature



Recommended PCB Configuration




Truth Table (Digital Attenuator)

| Control Inputs | | | | | |
|----------------|----|----|----|----|-------------|
| C1 | C2 | C3 | C4 | C5 | Attenuation |
| 0 | 0 | 0 | 0 | 0 | Reference |
| 1 | 0 | 0 | 0 | 0 | 0.5 dB |
| 0 | 1 | 0 | 0 | 0 | 1 dB |
| 0 | 0 | 1 | 0 | 0 | 2 dB |
| 0 | 0 | 0 | 1 | 0 | 4 dB |
| 0 | 0 | 0 | 0 | 1 | 8 dB |
| 1 | 1 | 1 | 1 | 1 | 15.5 dB |

0 = TTL Low; 1 = TTL High

Attenuation Accuracy vs. Frequency 0.5, 1, 2 dB Bits




Digital Attenuator
15.5 dB, 5-Bit, TTL Driver, DC-2.0 GHz


Rev. V7

Typical Performance Curves


Attenuation Accuracy vs. Frequency 4, 8 dB Bits and Full Attenuation




VSWR vs. Frequency Reference Loss, 0.5, 1, 2 dB Bits



VSWR vs. Frequency 4, 8 dB Bits and Full Attenuation



Lead-Free, CR-12 Ceramic Package[†]



[†] Reference Application Note M538 for lead-free solder reflow recommendations.

M/A-COM Technology Solutions Inc. All rights reserved.

Information in this document is provided in connection with M/A-COM Technology Solutions Inc ("MACOM") products. These materials are provided by MACOM as a service to its customers and may be used for informational purposes only. Except as provided in MACOM's Terms and Conditions of Sale for such products or in any separate agreement related to this document, MACOM assumes no liability whatsoever. MACOM assumes no responsibility for errors or omissions in these materials. MACOM may make changes to specifications and product descriptions at any time, without notice. MACOM makes no commitment to update the information and shall have no responsibility whatsoever for conflicts or incompatibilities arising from future changes to its specifications and product descriptions. No license, express or implied, by estoppel or otherwise, to any intellectual property rights is granted by this document.

THESE MATERIALS ARE PROVIDED "AS IS" WITHOUT WARRANTY OF ANY KIND, EITHER EXPRESS OR IMPLIED, RELATING TO SALE AND/OR USE OF MACOM PRODUCTS INCLUDING LIABILITY OR WARRANTIES RELATING TO FITNESS FOR A PARTICULAR PURPOSE, CONSEQUENTIAL OR INCIDENTAL DAMAGES, MERCHANTABILITY, OR INFRINGEMENT OF ANY PATENT, COPYRIGHT OR OTHER INTELLECTUAL PROPERTY RIGHT. MACOM FURTHER DOES NOT WARRANT THE ACCURACY OR COMPLETENESS OF THE INFORMATION, TEXT, GRAPHICS OR OTHER ITEMS CONTAINED WITHIN THESE MATERIALS. MACOM SHALL NOT BE LIABLE FOR ANY SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES, INCLUDING WITHOUT LIMITATION, LOST REVENUES OR LOST PROFITS, WHICH MAY RESULT FROM THE USE OF THESE MATERIALS.

MACOM products are not intended for use in medical, lifesaving or life sustaining applications. MACOM customers using or selling MACOM products for use in such applications do so at their own risk and agree to fully indemnify MACOM for any damages resulting from such improper use or sale.

5

M/A-COM Technology Solutions Inc. (MACOM) and its affiliates reserve the right to make changes to the product(s) or information contained herein without notice.
Visit www.macom.com for additional data sheets and product information.